



Woodworking machinery at its best!

Replacing a motor on W691 or W692 Dust Extractor

Identify which model you have:

Model A has 4 terminals on the switch and 2 wires from the motor.

Model B has 5 terminals on the switch and 4 wires from the motor.

All replacement motors have 4 wires.

Instructions for Model A - Using KJD12 switch

Blue wire from plug - Switch terminal 1

Brown wire from plug - Switch terminal 3

Green /Yellow from plug - Earth point on motor body

Blue wire from motor - Switch terminal 2

White wire (either one) from motor - Switch terminal 4

Brown wire from motor - Other White wire from motor

Instructions for Model B - Using KJD17B switch

Blue wire from plug - Switch terminal 13

Brown wire from plug - Switch terminal 23

Green /Yellow from plug - Earth point on motor body

Blue wire from motor - Switch terminal 14

Brown wire & White wire (either one) from motor - Switch terminal 24

Other White wire from motor - Switch terminal A1 (Remote Trip)

Tel. 01530 516926 Fax. 01530 516929 email; sales@charnwood.net

Website: www.charnwood.net

VAT GB 290 2170 80

Charnwood, Cedar Court, Walker Road, Bardon, Leicestershire, LE67 1TU, England

Charnwood is a division of Cooks Export Services Ltd, Registration No:1316450